

■ ■ ■
TX-8220

ONKYO®

THE HEART OF ENTERTAINMENT

TX-8220

STEREO AMPLIFIER

With Hi-fi Power On Tap, the TX-8220 Offers You More

Universal connectivity meets pure analog amplification performance in a simple hub that sounds extremely natural and controlled. All the essentials are covered with digital audio inputs for TV and BD/DVD player connection, along with five analog line-level inputs for CD player and any other analog or digital source. The TX-8220 also takes value up a notch with MM phono input for turntable, DAB+ and FM/RDS radio tuners with 40 presets, and built-in *Bluetooth*® technology. Boasting clean, minimal design with maximum versatility, the TX-8220 is great value.





TX-8220

STEREO AMPLIFIER



PREMIUM AUDIO CO.

©2024 PREMIUM AUDIO CO. ALL RIGHTS RESERVED.



HIGH CURRENT AND LOW IMPEDANCE AMPLIFIER ARCHITECTURE

Onkyo's high-current low-impedance WRAT design uses a massive EI transformer to drive your speakers accurately, even under heavy loads.

Discrete amplification stage and customized capacitors deliver ample driving power with low distortion.

High current grips the speaker cones for more accurate control, restoring vitality and detail to music. Wide-range non-phase-shift circuitry, meanwhile, clearly focuses the audio image.

CONNECT ANY BLUETOOTH DEVICE, TURNTABLE, CD PLAYER, TV, AND MEDIA STREAMER

Aimed at music and film lovers that want to add great sound to a variety of media sources, the TX-8220 comes extensively equipped with digital and analog audio connections.

The receiver is one of the few at this price to include a quality MM phono stage for your turntable. It also has digital inputs to route audio from TV through amp and speakers.

Finally, with low-latency Bluetooth 4.1 wireless technology, you can stream almost any audio that's playing on your smartphone, tablet, laptop, or PC applications.

A/B SPEAKER POSTS FOR MULTI-ROOM AUDIO

TX-8220 features two sets of speaker posts enabling connection of two pairs of speakers.

The receiver is designed to drive either a single pair of speakers rated at 4-16 Ω , or two pairs of 8-16 Ω speakers, allowing you to enjoy the same audio source in two rooms at once, or to easily switch between two sets of speakers.

MAIN FEATURES

- Amplification power :
2* 100 W/Ch (6 Ω , 1 kHz, 10%, 1 Channel Driven, IEC)
- 192 kHz/24-bit* (PCM1754) Digital-to-Analog Converter
- Bluetooth® Audio Streaming Technology for Almost Any Device
- DAB+ and FM/RDS Radio Tuners with 40 Station Presets
- Direct Mode for Source-Authentic Audio Reproduction
- Phono Input with MM Equalizer
- Tone control : +/- 12dB @100Hz (Bass)
+/- 12dB @10KHz (Treble)
- Subwoofer Pre-Out

Frequency Response	10 Hz-100 kHz/+1 dB, -3 dB (Direct Mode)
THD (Total Harmonic Distortion)	0.08% (20 Hz-20 kHz, Half Power)
Signal-to-Noise Ratio	100 dB (IHF-A, Line In, Speaker Out) 93 dB (IHF-A, Phono In, Speaker Out)
Input Sensitivity and Impedance	Line 450 mV/40 k Ω Phono MM 10 mV/50 k Ω (IHF-A)
Rated RCA Output Level and Impedance	420 mV/2.2 k Ω (Line-Out) 2.8 mV/3.3 k Ω (Subwoofer Pre-Out)
Headphone output impedance	390 Ω
Headphone Rated Output	60 mW (32 Ω , 1 kHz, 10%)
Power Supply	AC 220-240 V, 50/60 Hz
Power Consumption	Standby 0.4 W No sound 20W
Product Dimensions (W x H x D)	435 x 149 x 328 mm
Product Weight	7 kg
Carton Dimensions (W x H x D)	533 x 234 x 401 mm
Carton Weight	8.8 kg
Supplied Accessories	Indoor FM/DAB+ antenna Instruction manual Remote controller AAA (R03) batteries x 2
SKU	TX8220BMMP
EAN	4573211153163

WRAT WIDE RANGE AMPLIFIER
TECHNOLOGY

192 kHz
24-bit



Due to a policy of continuous product improvement, Onkyo reserves the right to change specifications and appearance without notice. Some services are not selectable or not available in some areas